

TOWARDS THE THEORY OF CONTROL IN OBSERVABLE QUANTUM SYSTEMS

V. P. BELAVKIN

ABSTRACT. The fundamental mathematical definitions of the controlled feedback Markov dynamics of quantum-mechanical systems are introduced with regard to the dynamical reduction and filtering of quantum states in the course of quantum measurement in either discrete or continuous real time. The concept of sufficient coordinates for the description of *a posteriori* quantum states in a given class is introduced and it is proved that they form a classical Markov process with values in either state operators or state vector space. The general problem of optimal control of a quantum-mechanical system is discussed and the corresponding Bellman equation in the space of sufficient coordinates is derived. The results are illustrated in the example of control of the semigroup dynamics of a quantum system that is instantaneously observed at discrete times and evolves between measurement times according to the Schrödinger equation.

1. INTRODUCTION

The encouraging outlook for the application of coherent quantum optics (lasers) for communications and control has been recently stimulated by the steadily growing demands for greater accuracy of observation and monitoring, particularly under the “extreme” conditions of very faint signals at extremely great (astronomical) distances. On the other hand, instances of the successful exploitation of mathematical methods from information and control theory for the investigation of many physical phenomena in the microscopic world have also stimulated interest in the theoretical study, using general cybernetic principles, of the possibilities of dynamical systems described at the quantum-mechanical level [19][15][16][1][4]. It has been shown in [9] that it is natural to regard many physical problems as control problems for distributed systems described by standard quantum-mechanical equations. In particular, the possibility of the transition of a physical system from one microscopic state to another can be investigated [8] by the methods of the theory of controllability on Lie groups generated by the Schrödinger equation with a controlled Hamiltonian.

General problems in the theory of quantum dynamical systems with observation, control and feedback channels can be handled on the basis of the recent development [2] of an operational theory of open-loop quantum systems, for which the mathematical formalism was set down in [10] [13]. The investigation, undertaken in [3], of the dynamical observation and feedback control optimization problems for such systems has provided a means for solving these problems in the case of linear

Date: April 8, 1981.

Key words and phrases. Quantum Systems, Quantum Observation, Quantum Filtering, Quantum Control.

Markov systems of the boson type, in particular for a controllable and observable quantum oscillator [4]. This work was based on the multistage quantum-statistical decision theory originally described in [5][6] for the problems of the optimal dynamical measurement and control of classical (i.e., commutative) Markov processes with quantum observation channels.

In the present article we describe a simplified problem of optimal feedback control of quantum dynamical systems which does not involve quantum-statistical decision theory. Here the observable subsystem at the output of the observable channel is regarded as classical and amendable to description at the macroscopic level, whereas the controlled entity remains a quantum dynamical system. In other words, we assume here, in contrast with [3][5][6], that the “instrument” at the output of the quantum-mechanical system is given, rather than to be optimized, and it is required only to find the optimal macroscopic feedback for a given performance criteria. The results obtained in this setting are special in relation to [4][2][3] as they correspond to the semiclassical case of commutativity of the algebra of output observables. They nonetheless deserve special consideration both from the methodological and from the practical point of view when the observation channels are given and cannot be optimized for the optimal feedback control purpose.

2. CONTROLLABLE QUANTUM DYNAMICAL SYSTEMS WITH OBSERVATION

Here we introduce the mathematical concept of controllable quantum system with observation channel on the basis of the operational theory on open-loop physical systems and quantum processes [2][10][13]. Such systems are open by the definition, and the necessary concepts borrowed from the algebraic theory of open quantum systems are described in the Appendix.

Let $\mathcal{H}$ be the Hilbert space of representation of a certain quantum-mechanical system regarded as an observable and controllable system and let $\mathfrak{A}$ be the von Neumann algebra of admissible physical quantities $Q \in \mathfrak{A}$ which is generated (see Appendix 1) by the dynamical variables of this system, acting as operators in $\mathcal{H}$. The pair $\{\mathcal{H}, \mathfrak{A}\}$ plays the role of a measurable space $\{X, \mathcal{A}\}$ representing [14] the corresponding classical dynamical system in the phase space X of its point states, endowed with the Borel σ -algebra $\mathcal{A}$ of admissible events $A \in \mathcal{A}$. The simple systems normally treated in traditional texts on quantum mechanics, for example [17], correspond to the algebras $\mathfrak{A} = \mathcal{B}(\mathcal{H})$ of all bounded operators in $\mathcal{H}$, but the models that emerge from quantum field theory and statistical mechanics [12] are described by the more general algebras $\mathfrak{A}$.

Normal states of the quantum-mechanical system at every time $t \in \mathbb{R}$ are determined by the linear functionals $\varrho_t : Q \mapsto \langle \rho_t, Q \rangle$ of the quantum-mechanical expectations $\langle Q \rangle_t = \langle \rho_t, Q \rangle$ of all the physical quantities $Q \in \mathfrak{A}$ for this system, and are described by the densities ρ_t as the positive elements associated with von Neumann algebra $\mathfrak{A}$ (see Appendix 2). In the case of semifinite algebras [11], as in the simple case $\mathfrak{A} = \mathcal{B}(\mathcal{H})$, the states ϱ_t are usually represented by the trace one operators ρ_t in $\mathfrak{A}$ (or affiliated with $\mathfrak{A}$) as

$$(2.1) \quad \varrho_t(Q) = \text{tr} \{ \rho_t Q \} \equiv \langle \rho_t, Q \rangle.$$

The Master evolution $t \mapsto \varrho_t$ of a quantum-mechanical system controlled on each time interval $[t, t+\tau)$ by a segment $u_t^\tau = \{u(r) : r \in [t, t+\tau)\}$ of certain parameters $u(t)$ is usually described by linear unital completely positive transformations of the

states

$$(2.2) \quad \varrho_t \in \mathfrak{A}_* \mapsto \varrho_t M_t^\tau(u_t^\tau) \equiv \varrho_{t+\tau}(u_t^\tau) \in \mathfrak{A}_* \quad \forall t \in \mathbb{R}, \tau > 0.$$

They are determined by the composition of the functionals $\varrho_t : \mathfrak{A} \mapsto \mathbb{C}$ with controlled transfer operators $M_t^\tau(u_t^\tau)$ as the maps $\mathfrak{A} \mapsto \mathfrak{A}$ defined in the Appendix 3. The Markov family $\{M_t^\tau\}_{t \in \mathbb{R}, \tau > 0}$ of these maps must satisfy the consistency condition

$$(2.3) \quad M_r^\tau(u_r^\tau) M_{r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}) = M_r^{\tau+\tau'}(u_r^{\tau+\tau'}) \quad \forall r \in \mathbb{R}, \quad \tau, \tau' > 0,$$

as quantum analog of the controlled Chapman-Kolmogorov equation. Here $u_r^\tau = \{u(r + \tau')\}_{\tau' < \tau}$ is a segment of an admissible control function $u(t) \in U(t)$ of length $\tau > 0$ and $u_r^{\tau+\tau'}$ denotes the composition $(u_r^\tau, u_{r+\tau}^{\tau'})$ of segments u_r^τ and $u_{r+\tau}^{\tau'}$. Note that for stationary (time shift-invariant) systems, where $U(t) = U$, (2.3) specifies the cocycle conditions for transfer operators $M^\tau(u^\tau) = M_r^\tau(u_r^\tau)$ independent of r with respect to the shift $u^\tau \mapsto u_r^\tau$ given by $u_r(t) = u(t + r)$.

In the spatial case of transfer operators $M_t^\tau(u_t^\tau)$ specified by controllable propagators $T(u_t^\tau) : \mathcal{H} \mapsto \mathcal{H}$ satisfying the condition corresponding to (2.2),

$$T_{r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}) T_r^\tau(u_r^\tau) = T_r^{\tau+\tau'}(u_r^{\tau+\tau'}),$$

the dynamics $\varrho_t \mapsto \varrho_{t+\tau}(u_t^\tau)$ for the vector states $\langle \rho_t, Q \rangle = \langle \psi_t | Q \psi_t \rangle$ is described by the state-vector transformations

$$\psi_t \in \mathcal{H} \mapsto T_t^\tau(u_t^\tau) \psi_t \equiv \psi_{t+\tau}(u_t^\tau) \in \mathcal{H} \quad \forall t \in \mathbb{R}, \tau > 0.$$

Such transformations can be obtained, for example, as the fundamental solutions of the time-dependant Schrödinger equation with a perturbing force $u(t)$, for which the isometric operators $T_t^\tau(u_t^\tau)$ are unitary, and $M_t^\tau(u_t^\tau)$ are the Heisenberg transformations

$$M_t^\tau(u_t^\tau) Q = T_t^\tau(u_t^\tau)^\dagger Q T_t^\tau(u_t^\tau).$$

The open-loop input-output quantum dynamical systems of the kind specified below as controllable systems with observation cannot, as a rule, be described in terms of propagators $T_t^\tau(u_t^\tau)$, because the measurements induce reductions and decoherence of quantum states which are described by more general transformations. In order to define such systems as quantum dynamical objects with the classical inputs $u(t)$ and outputs $v(t) \in V(t)$, we shall fix a pair of two-parameter families $\{U_t^\tau\}, \{V_t^\tau\}, t \in \mathbb{R}, \tau > 0$ of the Cartesian product subsets $U_t^\tau \subseteq \prod_{\tau' < \tau} U(t + \tau')$,

$V_t^\tau = \prod_{\tau' < \tau} V(t + \tau')$, satisfying the consistency condition

$$(2.4) \quad U_r^\tau \times U_{r+\tau}^{\tau'} = U_r^{\tau+\tau'}, \quad V_r^\tau \times V_{r+\tau}^{\tau'} = V_r^{\tau+\tau'}.$$

The elements $u_t^\tau \in U_t^\tau, v_t^\tau \in V_t^\tau$ are called the admissible segments of signals, and their Cartesian compositions should also be admissible in order to make sense, for example, of (2.3). The sets U_r^τ are usually endowed with Hausdorff product topologies, and the sets V_r^τ with Borel product σ -algebras, making them consistent with (2.4). Note that the continuous signals $u(t)$ and $v(t)$ on $t \in \mathbb{R}$ do not satisfy the conditions (2.4). In the time shift-invariant case U_r^τ and V_r^τ are given by the shift $t \mapsto t + r$ of the initial sets $U^\tau = U_0^\tau$ and $V^\tau = V_0^\tau$.

Definition 1. A controllable quantum dynamical system with observation is described by a family $\{\Pi_t^\tau\}_{t \in \mathbb{R}, \tau > 0}$ of controllable transfer-operator measures $\Pi_t^\tau(u_t^\tau, dv_t^\tau) : \mathfrak{A} \mapsto \mathfrak{A}$ (see Appendix 4) defined on the spaces $U_t^\tau \ni u_t^\tau, V_t^\tau \supseteq dv_t^\tau$ and satisfying the condition

$$(2.5) \quad \Pi_r^\tau(u_r^\tau, dv_r^\tau) \Pi_{r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, dv_{r+\tau}^{\tau'}) = \Pi_r^{\tau+\tau'}(u_r^{\tau+\tau'}, dv_r^{\tau+\tau'})$$

for any $r \in \mathbb{R}$, $\tau, \tau' > 0$, where $u_r^{\tau+\tau'} = (u_r^\tau, u_{r+\tau}^{\tau'})$, $dv_r^{\tau+\tau'} = dv_r^\tau \times dv_{r+\tau}^{\tau'}$.

The superoperators $\Pi_t^\tau(u_t^\tau, dv_t^\tau)$ are assumed to be continuous in u_t^τ , σ -additive with respect to dv_t^τ (in the strong operator sense) and in the time shift-invariant case not to depend explicitly on t [the index t in the condition (2.5) specifying the cocycle dependence on τ can now be omitted].

Due to positivity $Q \in \mathfrak{A}_+ \mapsto \Pi_t^\tau(u_t^\tau, dv_t^\tau) Q \in \mathfrak{A}_+$ and the normalization condition $\Pi_t^\tau(u_t^\tau, V_t^\tau) = M_t^\tau(u_t^\tau)$, the mappings Π_t^τ determine, for a given instantaneous state $\varrho_t \in \mathfrak{A}_*$ and control function u_t^τ , the future ($\tau > 0$) states

$$(2.6) \quad \varrho_{t+\tau}(u_t^\tau, dv_t^\tau) = \varrho_t \Pi_t^\tau(u_t^\tau, dv_t^\tau)$$

of the quantum-mechanical process, normalized to the probabilities

$$(2.7) \quad \pi_t^\tau(u_t^\tau, dv_t^\tau) = \langle \varrho_t, \Pi_t^\tau(u_t^\tau, dv_t^\tau) I \rangle \equiv \varrho \Pi_t^\tau(u_t^\tau, dv_t^\tau) I$$

of the events $v_t^\tau \in dv_t^\tau$. The ratio of (2.6) to (2.7) determines conditional states, depending in general non-linearly on $\varrho = \varrho_t$:

$$(2.8) \quad \varrho_t^\tau = \frac{\varrho \Pi_t^\tau(u_t^\tau, dv_t^\tau)}{\varrho \Pi_t^\tau(u_t^\tau, dv_t^\tau) I}.$$

Note that the normalized conditional states are well-defined only for the measurable events $dv_t^\tau \subseteq V_t^\tau$ of non-zero probability (2.7) with which the system transfers from the state $\varrho_t = \varrho$ as a result of the control action u_t^τ and the observation dv_t^τ on an interval of length τ . If the event $dv_t^\tau = V_t^\tau$ is certain, $\pi_t^\tau(u_t^\tau, dv_t^\tau) = 1$, the states (2.8) are unconditional such that ϱ_t^τ coincide with *a priori* states $\varrho_{t+\tau}(u_t^\tau)$, whose controlled evolution is linear. Such evolution is described by expression (2.2), in which $M_t^\tau(u_t^\tau) = \Pi_t^\tau(u_t^\tau, V_t^\tau)$ denotes controllable transforms of the open-loop quantum-mechanical system, corresponding to the absence of observation. However in general the process of precise measurement of the output signal v_t^τ on an interval of length $\tau > 0$ takes the quantum system from *a priori* state $\varrho = \varrho_t$ to the *a posteriori* state $\varrho_t^\tau = \varrho M_{\rho,t}^\tau(u_t^\tau, v_t^\tau)$, where the quasilinear mapping $\varrho \mapsto \varrho M_{\rho,t}^\tau(u_t^\tau, v_t^\tau)$ is given by expression (2.8) in the limit $dv_t^\tau \downarrow \{v_t^\tau\}$ almost everywhere with respect to the measure (2.7). For example, let the measures Π_t^τ have the density functions

$$(2.9) \quad \Pi_t^\tau(u_t^\tau, dv_t^\tau) = \int_{dv_t^\tau} P_t^\tau(u_t^\tau, v_t^\tau) \mu_t^\tau(u_t^\tau, dv_t^\tau),$$

where $P_t^\tau(u_t^\tau, v_t^\tau) : \mathfrak{A} \mapsto \mathfrak{A}$ denotes completely positive superoperators [see the Appendix, (A.4)], say, of the form (3.10), continuous with respect to u_t^τ and integrable with respect to v_t^τ in the strong operator sense with respect to specified positive

measures μ_t^τ on V_t^τ . Then the *a posteriori* transfer operators $M_{\rho,t}^\tau(u_t^\tau, v_t^\tau)$ coincide, up to normalization, with $P_t^\tau(u_t^\tau, v_t^\tau)$:

$$(2.10) \quad M_{\rho,t}^\tau(u_t^\tau, v_t^\tau) = \frac{P_t^\tau(u_t^\tau, v_t^\tau)}{\langle \rho, P_t^\tau(u_t^\tau, v_t^\tau) I \rangle},$$

where the ratio is defined for those $u_t^\tau \in U_t^\tau$, $v_t^\tau \in V_t^\tau$ for which the densities

$$(2.11) \quad p_t^\tau(u_t^\tau, v_t^\tau) = \langle \rho, P_t^\tau(u_t^\tau, v_t^\tau) I \rangle \equiv \varrho P_t^\tau(u_t^\tau, v_t^\tau) I$$

of the probability measure (2.7) with respect to μ_t^τ are non-vanishing.

The following theorem states that the *a posteriori* mapping (2.10) in fact determines the state-valued classical Markov process, which was introduced in the classical case by Stratonovich in [20] (He called this probability measure-valued process secondary, or conditional (*a posteriori*) Markov process).

Theorem 1. *The family $\{M_{\rho,t}^\tau\}$ of a posteriori transfer operators $M_{\rho,t}^\tau(u_t^\tau, v_t^\tau)$ satisfies, with respect to the operator composition, the consistency condition*

$$(2.12) \quad M_{\rho,r}^\tau(u_r^\tau, v_r^\tau) M_{\rho',r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, v_{r+\tau}^{\tau'}) = M_{\rho,r}^{\tau+\tau'}(u_r^{\tau+\tau'}, v_r^{\tau+\tau'})$$

almost everywhere under the measure (2.7), where ρ' is the density of $\varrho' = \varrho M_{\rho,r}^{\tau'}(u_r^\tau, v_r^\tau)$.

Proof. It is required to verify the property (2.12) for conditional mappings (2.8), for which it follows at once from the definition and (2.5). Then it applies also in the single point limit $dv_t^\tau \downarrow \{v_t^\tau\}$. In the case (2.9) the condition (2.12) is simply verified by computing the product (2.12) of the *a posteriori* transfer operators (2.10); for this purpose it is necessary to invoke the corresponding condition

$$(2.13) \quad P_r^\tau(u_r^\tau, v_r^\tau) P_{r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, v_{r+\tau}^{\tau'}) = P_r^{\tau+\tau'}(u_r^{\tau+\tau'}, v_r^{\tau+\tau'}).$$

It is sufficient to require this composition condition for $V_t^{\tau+\tau'}$ almost everywhere (mod μ_t^τ) and this will guarantee the satisfaction of condition (2.4) if

$$\mu_r^\tau(u_r^\tau, dv_r^\tau) \mu_{r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, dv_{r+\tau}^{\tau'}) = \mu_r^{\tau+\tau'}(u_r^{\tau+\tau'}, dv_r^{\tau+\tau'}).$$

□

Remark 1. *If the superoperator densities P_t^τ of the transition measures (2.9) preserve unity: $P_t^\tau(u_t^\tau, v_t^\tau) I = p_t^\tau(u_t^\tau, v_t^\tau) I$, the ratio (2.10) determines ρ -independent transfer operators $M_t^\tau(u_t^\tau, v_t^\tau)$ describing the controllable quantum dynamics of a system with two inputs u and v . The second is an observable stochastic process with probability measures $\pi_t^\tau(u_t^\tau, v_t^\tau) = p_t^\tau(u_t^\tau, v_t^\tau) \mu_t^\tau(u_t^\tau, v_t^\tau)$ independent of the state of the system. The *a posteriori* mappings (2.8) in this case are linear, $\varrho_t^\tau = \varrho M_t^\tau(u_t^\tau, v_t^\tau)$, almost everywhere under the measure π_t^τ .*

3. SUFFICIENT COORDINATES OF QUANTUM-MECHANICAL SYSTEMS

The description of the dynamics of simple closed-loop quantum-mechanical systems for a certain class of initial states is known to be often reducible to the determination of the time evolution of certain coordinates, the role of which can be taken, for example, by vectors $\psi \in \mathcal{H}$, if only vector initial states are considered. Some aspects of the controllability of closed-loop quantum-mechanical systems described by a sufficient coordinate $\psi_t \in \mathcal{H}$, satisfying the controlled Schrödinger equation have been recently investigated in [8].

The concept of sufficient coordinates, which is introduced below for general controllable quantum dynamical systems with observation and is intimately related to the classical notion of sufficient statistics [20], plays an even greater role for quantum control theory than the analogous concept in stochastic control theory, because it permits control problems for quantum-mechanical systems to be reduced to classical control problems with localized or distributed parameters.

Definition 2. Let X be a measurable space¹, and let $\{\varrho_{x,t}\}_{x \in X, t \in \mathbb{R}}$ be a family of states given, for every $t \in \mathbb{R}$, by a measurable mapping $x \mapsto \varrho_{x,t}$ of the space X into the space of states $\varrho_{x,t} \in \mathfrak{A}_*$ of a quantum-mechanical system at time t such that the controlled evolution (2.5) of the system during an observation leaves this family up to a normalization $\pi_{x,t}^\tau$ invariant:

$$(3.1) \quad \varrho_{x,t} \Pi_t^\tau(u_t^\tau, dv_t^\tau) = \pi_{x,t}^\tau(u_t^\tau, dv_t^\tau) \varrho_{f_{x,t}^\tau(u_t^\tau, v_t^\tau), t+\tau}$$

Then $x \in X$ is called a sufficient coordinate for $\{\varrho_{x,t}\}$, the controlled stochastic evolution of which $x \in X \mapsto f_{x,t}^\tau(u_t^\tau, v_t^\tau) \equiv x_t^\tau \in X$ is described by the mappings $f_{x,t}^\tau : U_t^\tau \times V_t^\tau \rightarrow X$, continuous with respect to $u_t^\tau \in U_t^\tau$ and measurable with respect to $v_t^\tau \in V_t^\tau$ almost everywhere under the measure

$$\pi_{x,t}^\tau(u_t^\tau, dv_t^\tau) = \langle \rho_x, \Pi_t^\tau(u_t^\tau, dv_t^\tau) I \rangle.$$

Proceeding from (3.1) taken in the limit $dv_t^\tau \searrow \{v_t^\tau\}$, we note that the density operators $x = \rho$ form the sufficient coordinate space for the family of all normal states ϱ on $\mathfrak{A}$. It is given by the *a posteriori* mapping $f_{\rho,t}^\tau(u_t^\tau, v_t^\tau) = M_{\rho,t}^\tau(u_t^\tau, v_t^\tau)_* \rho$, provided only [as in the case (2.9)] that there exists the derivative

$$(3.2) \quad M_{\rho,t}^\tau(u_t^\tau, v_t^\tau) = \frac{\Pi_t^\tau(u_t^\tau, dv_t^\tau)}{\pi_{\rho,t}^\tau(u_t^\tau, dv_t^\tau)}.$$

as the limit $dv_t^\tau \searrow \{v_t^\tau\}$.

Theorem 2. The mappings $f_{x,t}^\tau$ in (3.1) define a sufficient statistics $x_t^\tau = f_{x,t}^\tau(u_t^\tau, v_t^\tau)$ for $\varrho_t \in \{\varrho_{x,t}\}_{x \in X}$ in the sense that the *a posteriori* states $\varrho_t^\tau = \varrho M_{\rho,t}^\tau(u_t^\tau, v_t^\tau)$ are determined for such $\varrho = \varrho_{x,t}$ as $\varrho_t^\tau = \varrho_{x_t^\tau, t+\tau} \forall \tau > 0$. Moreover, the transition probabilities

$$(3.3) \quad \pi_{x,t}^\tau(u_t^\tau, dx') = \langle \rho_x, \Pi_{x,t}^\tau(u_t^\tau, dx') \rangle,$$

from $x_t = x$ into $dx' \ni x_t^\tau$, defined by

$$\Pi_{x,t}^\tau(u_t^\tau, dx') = \Pi_t^\tau(u_t^\tau, f_{x,t}^{-1}(u_t^\tau, dx')) ,$$

$$(3.4) \quad f_{x,t}^{-1}(u_t^\tau, dx') = \{v_t^\tau : f_{x,t}^\tau(u_t^\tau, v_t^\tau) \in dx'\} ,$$

satisfy the Chapman-Kolmogorov equation

$$(3.5) \quad \int_{x' \in X} \pi_{x,r}^\tau(u_r^\tau, dx') \pi_{x',r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, dx'') = \pi_{x,r}^{\tau+\tau'}(u_r^{\tau+\tau'}, dx'')$$

for all $r \in \mathbb{R}$, $\tau, \tau' > 0$ and $u_r^{\tau+\tau'} = (u_r^\tau, u_{r+\tau}^{\tau'})$, so that the sufficient statistics form a controllable Markov process.

¹For all practical purposes it is always sufficient to assume that X is a standard Borel space, i.e. a complete separable metric space, also known as a Polish space (for example, $\mathbb{R}^n, \mathbb{C}^n$, or any countable set).

Proof. The existence of the sufficient statistics is determined by the *a posteriori* mapping according to the expression (2.8), which gives in correspondence with (3.1)

$$(3.6) \quad \varrho_t^\tau = \varrho M_{\varrho,t} (u_t^\tau, v_t^\tau) = \varrho_{f_{x,t}^\tau(u_t^\tau, v_t^\tau), t+\tau'}$$

for $\varrho = \varrho_{x,t}$, thus proving the first statement of Theorem 2. The transition mappings $x \mapsto f(u_t^\tau, v_t^\tau)$ in correspondence with the Theorem 1 satisfy the semigroup property with respect to their composition

$$(3.7) \quad f_{r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, v_{r+\tau}^{\tau'}) \circ f_r^\tau(u_r^\tau, v_r^\tau) = f_r^{\tau+\tau'}(u_r^{\tau+\tau'}, v_r^{\tau+\tau'}).$$

This yields, according to (2.5), the equation

$$(3.8) \quad \int_{x' \in X} \Pi_{x,r}^\tau(u_r^\tau, dx') \Pi_{x',r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, dx'') = \Pi_{x,r}^{\tau+\tau'}(u_r^{\tau+\tau'}, dx'')$$

in terms of the transfer-operator measures for the transitions $x \mapsto dx'$ specified in (3.3) and (3.4). For the states in the class $\{\varrho_{x,t}\}$, (3.8) is equivalent to the Chapman-Kolmogorov equation (3.5), as

$$(3.9) \quad \varrho_{x,t} \Pi_{x,t}^\tau(u_t^\tau, dx') = \pi_{x,t}^\tau(u_t^\tau, dx') \varrho_{x',t+\tau}$$

in accordance with (3.1). Thus equation (3.5) determines a Markov stochastic evolution $\hat{x}(t)$ of the sufficient coordinates $x(t) \in X$, which is described, according to the main Kolmogorov theorem (see, e.g. [10], p. 48 for a standard space X), a Markov probability measure in the functional Borel space of the trajectories $\{x(t)\}$. This completes the proof. $\square$

We now discuss in more detail the special case, in which the transition measures (2.9) have the superoperator densities

$$(3.10) \quad P_t^\tau(u_t^\tau, v_t^\tau) Q = F_t^\tau(u_t^\tau, v_t^\tau)^\dagger Q F_t^\tau(u_t^\tau, v_t^\tau)$$

with respect to a given consistent family of measures $\mu_t^\tau(u_t^\tau, dv_t^\tau)$. Here the operators $F_t^\tau(u_t^\tau, v_t^\tau)$ are assumed to satisfy the normalization condition

$$(3.11) \quad \int F_t^\tau(u_t^\tau, v_t^\tau)^\dagger F_t^\tau(u_t^\tau, v_t^\tau) \mu_t^\tau(u_t^\tau, dv_t^\tau) = I,$$

in the Hilbert space $\mathcal{H}$, as well as the composition condition

$$(3.12) \quad F_{r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, v_{r+\tau}^{\tau'}) F_r^\tau(u_r^\tau, v_r^\tau) = F_r^{\tau+\tau'}(u_r^{\tau+\tau'}, v_r^{\tau+\tau'}),$$

which guarantees the fulfillment of (2.13).

One can easily see that the *a posteriori* transfer operators (2.10) preserve the vectorial property of the states $\varrho_\psi(Q) = \langle \psi | Q \psi \rangle$ such that

$$\varrho_{\psi,t}^\tau(Q) = \langle \psi_t^\tau | Q \psi_t^\tau \rangle \equiv \varrho_{\psi_t^\tau}(Q),$$

where $\psi_t^\tau = T_{\psi,t}^\tau(u_t^\tau, v_t^\tau) \psi$ for any unit vector $\psi \in \mathcal{H}$, $\tau > 0$ and

$$(3.13) \quad T_{\psi,t}^\tau(u_t^\tau, v_t^\tau) = \frac{F_t^\tau(u_t^\tau, v_t^\tau)}{\|F_t^\tau(u_t^\tau, v_t^\tau) \psi\|}.$$

Corollary 1. *The normalized vectors $\psi \in \mathcal{H}, \|\psi\| = 1$ in the case (3.10) form the space X of sufficient coordinates $x = \psi$ specified by the *a posteriori* mappings $f_{\psi,t}^\tau(u_t^\tau, v_t^\tau) = T_{\psi,t}^\tau(u_t^\tau, v_t^\tau) \psi$ of the quasilinear form (3.13) for the family of all vectorial states ϱ_ψ .*

We note that the *a posteriori* propagators $T_{\psi,t}^\tau(u_t^\tau, v_t^\tau)$ satisfy the semigroup property (3.7):

$$(3.14) \quad T_{\psi',r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}, v_{r+\tau}^{\tau'}) T_{\psi,r}^\tau(u_r^\tau, v_r^\tau) = T_{\psi,r}^{\tau+\tau'}(u_r^{\tau+\tau'}, v_r^{\tau+\tau'}),$$

where $\psi' = T_{\psi,r}^\tau(u_r^\tau, v_r^\tau) \psi$. They are nonlinear (quasilinear), and in contrast with the linear operators $F_t^\tau(u_t^\tau, v_t^\tau)$ they preserve the norm in $\mathcal{H}$. Only in the case discussed at the end of Section 3, where $F_t^\tau(u_t^\tau, v_t^\tau)^\dagger F_t^\tau(u_t^\tau, v_t^\tau) = p_t^\tau(u_t^\tau, v_t^\tau) I$, the operators (3.13) are ψ -independent isometries $T_t^\tau(u_t^\tau, v_t^\tau) = F_t^\tau(u_t^\tau, v_t^\tau) / \sqrt{p_t^\tau(u_t^\tau, v_t^\tau)}$. We note, however, that the *a priori* transfer operators

$$(3.15) \quad M_t^\tau(u_t^\tau) Q = \int F_t^\tau(u_t^\tau, v_t^\tau)^\dagger Q F(u_t^\tau, v_t^\tau) \mu_t^\tau(u_t^\tau, dv_t^\tau)$$

determining the controllable Markov dynamics of the quantum system (2.9), (3.10) in the absence of observations, are not described by the propagators $T_t^\tau(u_t^\tau)$, with the exception of the degenerate case in which the *a posteriori* states coincide mod μ_t^τ with *a priori* states, i.e., actually do not depend on the results of the observations v_t^τ .

4. OPTIMAL QUANTUM FEEDBACK CONTROL

Let us now discuss the optimal control of a quantum dynamical system with observation $\{\Pi_t^\tau\}$. We assume that the performance of the system is measured at each time t by the mathematical expectation $\langle \rho_t, Q_t(u_t, dv_t) \rangle$ of a certain physical quantity $Q_t(u_t, dv_t) \in \mathfrak{A}$ which continuously depends in strong operator topology on the input state $u_t = \{u(t+\tau)\}_{\tau \geq 0}$ and on the output event $dv_t = d\{v(t+\tau)\}_{\tau > 0}$ according to the equation

$$(4.1) \quad Q_t(u_t, dv_t) = \Pi_t^\tau(u_t^\tau, dv_t^\tau) Q_{t+\tau}(u_{t+\tau}, dv_{t+\tau}) + S_t^\tau(u_t^\tau, dv_t^\tau).$$

Here $S_t^\tau(u_t^\tau, dv_t^\tau) \in \mathfrak{A}$ are Hermitian operators having the integral form

$$(4.2) \quad S_t^\tau(u_t^\tau, dv_t^\tau) = \int_0^\tau \Pi_t^{\tau'}(u_t^{\tau'}, dv_t^{\tau'}) S(u(t+\tau'), t+\tau') d\tau'$$

for a Hermitian operator-function $S(u, t) = S(u, t)^\dagger$ completely determining (4.1) for a certain boundary condition $Q_T(u_T, dv_T) = Q$ at the final time $T > t$. The conditions for the existence of the integral 4.2, its continuous dependence on u_t^τ , and its σ -additivity with respect to dv_t^τ , requiring the continuity in $u \in U$ and measurability in $t \in \mathbb{R}$ for the operator function $(u, t) \mapsto S(t, u) \in \mathfrak{A}$ under strong operator topology, are presumed to be fulfilled. The operator Q , specifying the terminal risk $\langle \rho_T, Q \rangle$, is assumed to be Hermitian-positive.

Definition 3. A measurable mapping $v_t \mapsto u_t(v_t) \in U_t$ is called a *non-anticipating control strategy* if its components $u(t+\tau, \cdot) : v_t \mapsto u(t+\tau)$ are determined by functions independent of $v_{t+\tau}$. It is called a *retarded control strategy* if all $u(t+\tau, \cdot)$ are determined by functions $v_t^{\tau'} \mapsto u(t+\tau, v_t^{\tau'})$ for some measurable $\tau' = \tau'(t+\tau) < \tau$. A non-anticipating strategy $u_t(\cdot)$ is called *admissible* if the integral

$$Q_t[u(\cdot)] = \int Q_t(u_t(v_t), dv_t)$$

exists in strong operator topology, and it is called optimal for an initial state $\varrho_t = \varrho$ if it realizes the extremum

$$(4.3) \quad q(\rho, t) = \inf_{u_t(\cdot) \in U_t(\cdot)} \langle \rho, Q_t[u_t(\cdot)] \rangle,$$

where $U_t(\cdot)$ is a certain set of admissible strategies $u_t(\cdot)$ [ε -optimal if $\langle \rho, Q_t[u_t(\cdot)] \rangle$ exceeds (4.3) at most by ε].

We note that in accordance with (4.1), a strategy $u_t(\cdot)$ is admissible with respect to $Q_t(\cdot, \cdot)$ if and only if its segments $u_{t+\tau}(\cdot)$ are admissible strategies with respect to $Q_{t+\tau}(\cdot, \cdot)$ for each fixed v_t^τ , and if there exists measure

$$(4.4) \quad \Pi_t^{u, \tau}(dv_t^\tau) = \int_{dv_t^\tau} \Pi_t^\tau(u_t^\tau(v_t^\tau), dv_t^\tau),$$

specifying the operator-valued integral

$$(4.5) \quad S_t^\tau[u_t^\tau(\cdot)] = \int_0^\tau \int_{V_t^\tau} \Pi_t^{u, \tau'}(dv_t^{\tau'}) S(t + \tau', u(t + \tau', v_t^{\tau'}))$$

for each strategy segment $u_t^\tau(\cdot)$. The latter holds for any delayed strategy that is admissible for a given boundary condition $Q_T(\cdot, \cdot) = Q$.

Theorem 3. *Let the sets $U_t^\tau(\cdot)$ of admissible strategy segments satisfy the condition*

$$(4.6) \quad U_t^\tau(\cdot) \times U_{t+\tau}^{\tau'}(\cdot) \subseteq U_t^{\tau+\tau'}(\cdot) \quad \forall t \in \mathbb{R}, \quad \tau, \tau' > 0.$$

Then the minimal risk (4.3) as a function of the density operator ρ and the time t satisfies the functional equation

$$(4.7) \quad q(\rho, t) = \inf_{u_t^\tau(\cdot) \in U_t^\tau(\cdot)} \left[\langle \rho, S_t^\tau[u_t^\tau(\cdot)] \rangle + \int \pi_{\rho, t}^{u, \tau}(dv_t^\tau) q(\rho(v_t^\tau), t + \tau) \right],$$

where $\pi_{\rho, t}^{u, \tau}(\cdot) = \langle \rho, \Pi_t^{u, \tau}(\cdot) I \rangle$, $\rho(v_t^\tau) = M_{\rho, t}^\tau(u_t^\tau(v_t^\tau), v_t^\tau)_* \rho$ denotes the probability measures (2.7) and a posteriori states (2.8) corresponding to an admissible strategy $u = u_t^\tau(\cdot)$ and an initial state $\varrho = \varrho_t$.

Proof. The proof of (4.7) generalizes the proof of the Bellman equation [7]. By substitution of (4.1) into (4.3) it reduces the minimization over $u_t(\cdot)$ by the successive minimization of (4.7), first on $u_{t+\tau}(\cdot)$ and then on $u_t^\tau(\cdot)$, which by condition (4.6) yields the same result as (4.3). Since the integral (4.5) does not depend on $u_{t+\tau}(\cdot)$ and by definition,

$$(4.8) \quad \varrho \Pi_t^{u, \tau}(dv_t^\tau) = \pi_{\rho, t}^{u, \tau}(dv_t^\tau) \varrho_{\rho, t}^{u, \tau},$$

the first minimization entails finding the second term of the minimized sum (4.7):

$$\inf_{u_{t+\tau}(\cdot) \in U_{t+\tau}(\cdot)} \int \pi_{\rho, t}^{u, \tau}(dv_t^\tau) \left\langle \rho(v_t^\tau), \int Q_t(u_t(v_t), dv_t) \right\rangle = \int \pi_{\rho, t}^{u, \tau}(dv_t^\tau) q(\rho(v_t^\tau), t + \tau).$$

□

In the case of a given boundary condition $q(\rho, t) = \langle \rho, Q \rangle$ the theorem proved above provides a constructive method of synthesizing an optimal or ε -optimal strategy $u_{\rho, t}^{T-t}(v_t^{T-t})$ by the successive minimization of (4.7) in reverse time. In this

case it is sufficient to restrict the discussion to Markov admissible strategies described by segments $u_{\rho,t'}^\tau(v_{t'}^\tau)$, $\tau = T - t$, depending on the *a priori* history v_t^τ only through the agency of their dependence on the *a posteriori* state $\varrho = \varrho_t^{t'-t}$ for any $t' > t$. Accordingly, the determination of the *a posteriori* quantum states ϱ_t^τ , which generate the *a posteriori* Markov process, enables us to reduce the optimal quantum control problem to the classical problem of stochastic control theory [20][7] with usual transition probabilities and final risk functions

$$s(\rho, t, u) = \langle \rho, S(t, u) \rangle, \quad q(\rho, T) = \langle \rho, Q \rangle,$$

determined by the operators of the corresponding quantum variables $S(t, u)$ and Q .

Let us consider the case in which the quantum states ϱ are considered in a certain class $\{\varrho_{x,t}\}$ for which sufficient coordinates exist.

Corollary 2. *Let $f_t^\tau : U_t^\tau \times V_t^\tau \mapsto X$ denote mappings satisfying the conditions of Theorem 2. Then in problem (4.3) for $\varrho \in \{\varrho_{x,t}\}$ it is sufficient to restrict the discussion to Markov strategies described by measurable mappings $u_t^\tau : X \times V_t^\tau \mapsto U_t^\tau$ satisfying the consistency condition*

$$(4.9) \quad \left(u_{x,r}^\tau(v_r^\tau), u_{x',r+\tau}^{\tau'}(v_{r+\tau}^{\tau'}) \right) = u_{x,r}^{\tau+\tau'}(v_r^{\tau+\tau'}),$$

where $x' = f_{x,t}^{u,\tau}(v_t^\tau) = f_{x,t}^\tau(u_t^\tau(v_t^\tau), v_t^\tau)$. In particular, the instantaneous control functions $u_x(\tau)$ for any $\tau \in [t, T]$ are determined by functions $u(\tau, x)$ of the point state x in accordance with the equation

$$(4.10) \quad u_x(t + \tau, v_t^\tau) = u(t + \tau, f_{x,t}^{u,\tau}(v_t^\tau)).$$

The foregoing assertion, which follows directly for the “maximum” sufficient coordinate $x(t) = \rho(t)$ from the optimality equation (4.7), is readily proved on the basis of the properties formulated for sufficient coordinates in Theorem 2.

The further simplification of problem (4.3) entails utilizing the specific properties of the Markov process $x(t) = f_{x,0}^{u,t}(v_0^t)$, the role of which is logically assigned to sufficient coordinates of the fewest possible dimensions.

For example, in the case where the generator for the transition probabilities $\pi_{x,t}^\tau(dx')$, defined as the t -continuous strong limit

$$(4.11) \quad L(t)q(t)(x) = \lim_{\tau \searrow 0} \int_X \pi_{x,t}^\tau(u_t^\tau, dx') (q(x', t + \tau) - q(x, t + \tau)),$$

exists on some set $\mathcal{D}(X)$ of bounded and measurable functions $x \mapsto q(x, t)$, depending continuously on t , the optimality equation (4.3) is written in the infinitesimal form

$$(4.12) \quad -\frac{\partial}{\partial t} q(x, t) = \inf_{u \in U} \{s(x, t, u) + L(t, u)q(t)(x)\},$$

where $s(x, t, u) = \langle \rho_{xt}, S(t, u) \rangle$. Equation (4.7), which represents the standard Bellman equation for controlled Markov processes in continuous time, can be used, together with a boundary condition $q(x, T) = \langle \rho_{x,T}, Q \rangle \in \mathcal{D}(X)$, to seek optimal or ε -optimal Markov control functions $u(t)$ directly as functions $u(t, x)$ of the instantaneous state x .

5. QUANTUM CONTROL WITH DISCRETE OBSERVATION

As an example here we consider the controlled dynamics of a simple quantum system described between discrete measurement times $T = \{t_k\}$ by the Schrödinger equation

$$(5.1) \quad i\hbar \frac{\partial}{\partial t} \psi(t) = H(t, u(t)) \psi(t), \quad t \in T.$$

Here $H(t, u)$ is the controlled Hamiltonian, i.e., a self-adjoint operator in $\mathcal{H}$ with a dense domain of definition $\mathcal{D} \subseteq \mathcal{H}$, written in the usual form

$$H(t, u) = H_0(t) + \sum_{i=1}^m u_i(t) H_i(t),$$

where $u_i(t) \in \mathbb{R}$; $H_i(t)$ are simple² functions of t . Under the stated assumption there exists a unique consistent family $\{T_t^\tau\}$ of unitary propagators $T_t^\tau(u_t^\tau)$, representing for any $\psi(t - \tau) = \varphi \in \mathcal{D}$, a solution of (5.1) between adjacent measurement times $t_k < t_{k+1}$ in the form $\psi(t) = T_{t-\tau}^\tau(u_{t-\tau}^\tau) \psi$, $t \in [t_k, t_{k+1})$, where $\lim_{\tau \searrow 0} \psi(t) = \psi$.

Let $E_{v,k}$ denote Hermitian projectors, which determine orthogonal decompositions $I = \sum_{v \in V_k} E_{v,k}$ of the unit operator in $\mathcal{H}$ and specify measurements at times t_k of quantum physical quantities described by self-adjoint operators

$$(5.2) \quad A_k = \sum_{v \in V_k} v E_{v,k}$$

with discrete spectra $V_k \subseteq \mathbb{R}$.

As a result of measurement of the quantity A_k there occurs a reduction [18] of the quantum state, $\varrho \mapsto \varrho \Pi_{v,k}$, $v \in V_k$, described by the superoperators $\Pi_{v,k} Q = E_{v,k} Q E_{v,k}$, which determines *a priori* transfer operators

$$(5.3) \quad \Pi_k Q = \sum_{v \in V_k} E_{v,k} Q E_{v,k}.$$

The states $\varrho_{v,k} = \varrho \Pi_{v,k}$ to which the system transfers instantaneously depending on the result of this measurement $v \in V_k$ are normalized to the probabilities $\pi_{v,k} = \langle \varrho, E_{v,k} \rangle$ of these transitions, where if $\varrho = \varrho_\psi$ is a vector state $\varrho_\psi(Q) = \langle \psi | Q \psi \rangle$, the states $\varrho_{v,k}$ are also vectorial, determined by the projections $\psi_{v,k} = E_{v,k} \psi$. The product $E_{v,k} T_t^\tau(u_t^\tau) = F_{v,t}^\tau(u_t^\tau)$ for $\tau = t_k - t$ determines a transformation $\psi(t) \mapsto E_{v,k} \psi(t_k)$ corresponding to the evolution (5.1) on the interval $[t, t_k]$ with subsequent measurement of the quantity A_k .

We introduce the notation $F_{v,k}(u_k) = F_{v,t_k}^{\tau_k}(u_{t_k}^{\tau_k})$, where $\tau_k = t_{k+1} - t_k$, and we set $V_t^\tau = \prod_{k \in K_t^\tau} V_k$, where $K_t^\tau = \{k : t_k \in [t, t + \tau)\}$ is the set of all indices of times

in the interval $(t, t + \tau)$ (in the case of an empty set $K_t^\tau = \emptyset$ we assume that V_t^τ consists of some single point $\{w\}$).

Proposition 1. *Let the set K_t^{s-t} be finite for any $t < s$. Then the chronological product*

$$(5.4) \quad F_{v,t}^{s-t}(u_t^{s-t}) = T_{t_1}^{s-t_1}(u_{t_1}^{s-t_1}) F_{v_1, l-1}(u_{l-1}) \dots F_{v_{k+1}, k}(u_k) F_{v_k, t}^{t_k-t}(u_t^{t_k-t}),$$

²In other words, having one-sided limits. For unbounded self-adjoint operators $H_i(t)$, $i = 0, \dots, m$, this means that $H(t, u(t))\psi$ is a simple function for any $\psi \in \mathcal{D}$.

where $k = \min K_t^{s-t}$, $l = \max K_t^{s-t}$, and $v = (v_k, \dots, v_l) = v_t^{s-t}$, determines controllable quantum dynamical system described by superoperators $\{\Pi_t^\tau\}$ of the form (2.9), (3.10):

$$(5.5) \quad \Pi_{v,t}^\tau(u_t^\tau) Q = F_{v,t}^\tau(u_t^\tau)^\dagger Q F_{v,t}^\tau(u_t^\tau),$$

under the counting measure $\mu_t^\tau = 1$ on $V_t^\tau \ni v$.

The proof is the verification of conditions (3.11) and (3.12), which take the form

$$(5.6) \quad \sum_{v \in V_t^\tau} F_{v,t}^\tau(u_t^\tau)^\dagger F_{v,t}^\tau(u_t^\tau) = I \quad \forall u_t^\tau \in U_t^\tau,$$

$$(5.7) \quad F_{v',r+\tau}^{\tau'}(u_{r+\tau}^{\tau'}) F_{v,r}^\tau(u_r^\tau) = F_{(v',v),r}^{\tau'+\tau}(u_r^{\tau'+\tau}),$$

where $v' \in V_{r+\tau}^{\tau'}$, $v \in V_r^\tau$. They are easily verified by induction, owing to the finiteness of the product (4.4).

Because of the spatial form (5.5) of the consistent family $\{\Pi_{v,t}^\tau\}$, on the basis of Corollary 1 we infer that the space X of normalized vectors $\psi \in \mathcal{H}$, $\|\psi\| = 1$ forms a space of sufficient coordinates, the *a posteriori* evolution $\psi \mapsto T_{v,t}^\tau(u_t^\tau, v_t^\tau) \psi$ of which is described by the nonlinear propagators (3.13): $T_{v,t}^\tau(u_t^\tau) / \|T_{v,t}^\tau(u_t^\tau) \psi\|$, and the *a priori* evolution by transfer operators of the form (3.15):

$$\Pi_t^\tau(u_t^\tau) Q = \sum_{v \in V_t^\tau} F_{v,t}^\tau(u_t^\tau)^\dagger Q F_{v,t}^\tau(u_t^\tau).$$

We give special consideration to the case of complete measurements described by the operators A_k with a non-degenerate spectrum.

Proposition 2. *Let $\{\psi_{v,k}\}_{v \in V_k}$ denote the complete orthonormal systems of eigenvectors of the operators A_k , and let $E_{v,k}$ be the corresponding one-dimensional projectors onto $\psi_{v,k}$. Then the *a posteriori* states at the times $\{t_k\}$ are vector states, which are completely determined by the last result of measurement $v_k \in V_k$:*

$$(5.8) \quad \langle \rho_t^{t_k-t}, Q \rangle = \langle Q \psi_{v_k,k}, \psi_{v_k,k} \rangle \quad \forall t < t_k, \quad \varrho = \varrho_t,$$

and the measurement process $\{v_k\}$ is a Markov process, which is described by the controllable transition probabilities

$$(5.9) \quad \pi_{v,k}(u_k, v_k) = |\langle \psi_{v_k,k+1} | T_k(u_k) \psi_{v_k,k} \rangle|^2,$$

where $T_k(u_k) = T_{t_k}^{\tau_k}(u_{t_k}^{\tau_k})$, $\tau_k = t_{k+1} - t_k$.

This proposition follows from the property

$$(5.10) \quad E_{v,k} Q E_{v,k} = \langle \psi_{v,k} | Q \psi_{v,k} \rangle E_{v,k}$$

of the one-dimensional orthogonal projection operators $E_{v,k}$ corresponding to the eigenvectors $\psi_{v,k}$, so that the application of any state ϱ to (5.5) at $t = t_k - \tau$ leads to (5.8), up to normalization. Since the *a posteriori* state (5.8) does not depend on the previous measurements, the conditional probability given by expression (5.9) for the event $v_{k+1} = v$ and fixed preceding results is Markovian.

In the proposition proved above, the controllable sufficient coordinate $x_k = v_k$ can be used, provided only that the quantum system is analyzed at discrete measurement times $\{t_k\}$.

We now consider the optimal control problem for a discretely observed quantum system. Let the control performance, as a function of the initial t , be described by an operator (4.1), which is determined by the integral (4.2) of some operator-valued function $S(t, u) : \mathcal{H} \mapsto \mathcal{H}$.

Proposition 3. *Under the conditions of Theorem 3, for a vector initial state ϱ_ψ the minimal risk*

$$(5.11) \quad q(\psi, t) = \inf_{u_t(\cdot) \in U_t(\cdot)} \int_{v_t} \langle \psi | Q_t(u_t(v_t), dv_t) \psi \rangle$$

in the intervals (t_k, t_{k+1}) between measurements satisfies the functional equation in variational derivatives

$$(5.12) \quad -\frac{\partial}{\partial t} q(\psi, t) = \inf_{u \in U(t)} \left(\|\psi\|_{S(t, u)}^2 + 2\hbar^{-1} \operatorname{Im} \langle \delta q(\psi, t) / \delta \psi | H(t, u) \psi \rangle \right),$$

where $\|\psi\|_S^2 = \langle \psi | S \psi \rangle$. At the measurement time instances $\{t_k\}$ it satisfies the recursive equation

$$(5.13) \quad q_k(\psi) = \inf_{u_k \in U_k} \left(\|\psi\|_{S_k(u_k)}^2 + \sum_{v \in V_{k+1}} \pi_{v, k}^u(\psi) q_{k+1}(\psi(v)) \right),$$

which determines the boundary values $q(t_k - 0, \psi) = q_k(\psi)$ for (5.12). Here $\pi_{v, k}^u(\psi) = \|T_{v, k}(u_k) \psi\|^2$, $\psi(v) = T_{v, k}(u_k) \psi / \sqrt{\pi_{v, k}^u(\psi)}$, and

$$(5.14) \quad S_k(u_k) = \int_0^\tau T_{t_k}^{t-t_k} (u_{t_k}^{t-t_k})^\dagger S(t, u(t)) T_{t_k}^{t-t_k} (u_{t_k}^{t-t_k}) dt.$$

Equation (5.12) is readily proved on the assumption of analyticity of the function $\psi \mapsto q(\psi, t)$ which is natural for a quadratic boundary condition $q(\psi, t) = \|\psi\|_Q^2$ at some final time T . Here (5.12) represents a functional version of the Bellman equation corresponding to the Schrödinger equation (5.1) and a quadratic transition cost function $S(t, u, \psi) = \|\psi\|_{S(t, u)}^2$. Equation (5.13) follows directly from (4.7) for $t = t_k$, $\tau = t_{k+1} - t_k$ and $\varrho = \varrho_\psi$ if it is taken into account that the integral (4.2) now has the form (5.14).

In conclusion we consider the optimal control problem described above in the complete measurement case. Making use of the fact that the process of complete measurement at discrete times $\{t_k\}$ induces a Markov sufficient coordinate $x_k = v_k$, from (5.13) we deduce the customary equation

$$(5.15) \quad q_k(v_k) = \inf_{u_k \in U_k} \left(s_k(u_k, v_k) + \sum_{v \in V_{k+1}} \pi_{v, k}(u_k, v_k) q_{k+1}(v) \right),$$

which describes the optimum risk for the control of a discrete Markov process $\{v_k\}$ with the transition probabilities (5.9), a cost function $s_k(u_k, v_k) = \|\psi_{v_k}\|_{S_k(u_k)}^2$ and a boundary condition of the form $q_k(v) = \|\psi_{v_k}\|_Q^2$. The solution of derived Bellman equation (5.15) can be easily modelled on a computer by standard dynamic programming methods for the piecewise-constant admissible strategies, for which $U_k = U(t_k) \subseteq \mathbb{R}^m$.

APPENDIX A. NOTATIONS, DEFINITIONS AND FACTS

- (1) Let $\{Q_i\}_{i \in I}$ be a family of self-adjoint operators acting in a complex Hilbert space $\mathcal{H}$. The von Neumann algebra generated by the family $\{Q_i\}$ is defined as the minimal weakly closed self-adjoint sub-algebra $\mathfrak{A}$ of bounded operators in $\mathcal{H}$ containing the spectral projectors of this operators, along with the unit operator I . It consists of all bounded operators that commute with the commutant $\{Q_i\}' = \{Q : QQ_i = Q_iQ \ \forall i \in I\}$, i.e., it is the second commutant $\mathfrak{A} = \{Q_i\}''$ of the family $\{Q_i\}$. The latter can be taken as the definition of the von Neumann algebra generated by the family $\{Q_i\}$ in the case of unbounded self-adjoint operators Q_i densely defined on a domain $\mathcal{D} \subseteq \mathcal{H}$. The simplest example of von Neumann algebra is the algebra $\mathcal{B}(\mathcal{H})$ of all bounded operators acting in $\mathcal{H}$ [11].
- (2) A state on a von Neumann algebra $\mathfrak{A}$ is defined as a linear ultraweakly continuous functional $\varrho : \mathfrak{A} \rightarrow \mathbb{C}$ (which will be denoted as $\varrho(Q) = \langle \rho, Q \rangle$) satisfying the positivity and normalization conditions

$$(A.1) \quad \langle \rho, Q \rangle \geq 0, \quad \forall Q \geq 0, \quad \langle \rho, I \rangle = 1$$

[$Q \geq 0$ signifies the nonnegative definiteness $\langle \psi | Q \psi \rangle \geq 0 \ \forall \psi \in \mathcal{H}$ called Hermitian positivity of Q]. It is described by the density operators ρ as the elements of the algebra $\mathfrak{A}$ with respect to a standard pairing $\langle \rho, Q \rangle$. The linear span of all states on $\mathfrak{A}$ is a Banach subspace $\mathfrak{A}_*$ of the dual space $\mathfrak{A}^*$, called predual to $\mathfrak{A}$ as $\mathfrak{A}_*^* = \mathfrak{A}$. A state ϱ is called vector state if $\langle \rho, Q \rangle = \langle \psi | Q \psi \rangle$ ($\varrho = \varrho_\psi$) for some $\psi \in \mathcal{H}$. Any state is a closed convex hull of vector states ϱ_ψ , $\|\psi\| = 1$. If on an algebra $\mathfrak{A}$ there exists a normal semi-finite trace $Q \mapsto \text{tr}\{Q\}$, then the states on $\mathfrak{A}$ can be described by the density operators $\rho \in \mathfrak{A}$ (or affiliated to $\mathfrak{A}$, if they are unbounded), determining ϱ by means of the bilinear form $\langle \rho, Q \rangle = \text{tr}\{\rho Q\}$. For the case $\mathfrak{A} = \mathcal{B}(\mathcal{H})$ the density operator ρ is any nuclear positive operator with unit trace [11].

- (3) Let $\mathfrak{A}_1, \mathfrak{A}_2$ be von Neumann algebras in respective Hilbert spaces $\mathcal{H}_1$ and $\mathcal{H}_2$, and let $M : \mathfrak{A}_2 \rightarrow \mathfrak{A}_1$ be a linear map that transforms the operators $Q_2 \in \mathfrak{A}_2$ into operators $Q_1 \in \mathfrak{A}_1$ (superoperator, in the terminology of [13]). We shall call the operator M a transfer operator if it is ultraweakly continuous, completely positive in the sense

$$(A.2) \quad \sum_{i,k=1} \left\langle \psi_i | M(Q_i^\dagger Q_k) \psi_k \right\rangle \geq 0, \quad \forall Q_i \in \mathfrak{A}_2, \quad \psi_i \in \mathcal{H}_1,$$

($i = 1, \dots, n < \infty$), and unity-preserving: $MI_2 = I_1$. In this case the composition $\varrho_1 M$ with a state $\varrho_1 : \mathfrak{A}_1 \rightarrow \mathbb{C}$ is a (normal) state $\mathfrak{A}_2 \rightarrow \mathbb{C}$ described by the predual action of the superoperator M on ρ_1 :

$$\langle \rho_1, M Q_2 \rangle = \langle M_* \rho_1, Q_2 \rangle, \quad \forall Q_2 \in \mathfrak{A}_2, \rho_1 \in \mathfrak{A}_1^*.$$

A transfer operator M is called spatial if

$$(A.3) \quad M Q_2 = T^\dagger Q_2 T \quad \text{or} \quad M_* \rho_1 = T \rho_1 T^\dagger,$$

where $T : \mathcal{H}_1 \rightarrow \mathcal{H}_2$ is a linear isometric operator, $T^\dagger T = I$, called the propagator, and $T^\dagger$ is the adjoint operator. Every transfer operator on $\mathfrak{A}_2 = \mathcal{B}(\mathcal{H}_2)$ has a decomposition as a closed convex hull of spatial transfer operators.

- (4) Let V be a measurable space, and $\mathcal{B}$ its Borel σ -algebra. A mapping $\Pi : dv \in \mathcal{B} \mapsto \Pi(dv)$ with values $\Pi(dv)$ in ultraweakly continuous, completely positive superoperators $\mathfrak{A}_2 \rightarrow \mathfrak{A}_1$ is called a transfer-operator measure if for any $\rho_1 \in \mathfrak{A}_1$, $Q_2 \in \mathfrak{A}_2$ the numerical function

$$\langle \Pi(dv)_* \rho_1, Q_2 \rangle = \langle \rho_1, \Pi(dv) Q_2 \rangle$$

of the set $dv \subseteq V$ is a countably additive measure normalized to unity for $Q_2 = I$. In other words, $\Pi(dv)$ is an operator-valued measure that is σ -additive in the weak (strong) operator sense and for $dv = V$ is equal to some transfer operator M . The quantum-state transformations $\rho_1 \mapsto \rho_2$ corresponding to ideal measurements are described by transfer-operator measures of the form

$$(A.4) \quad \Pi(dv) Q = F(v)^\dagger Q F(v) \mu(dv),$$

where $F(v)$ denotes linear operators $\mathcal{H}_1 \rightarrow \mathcal{H}_2$, the integral under a positive numerical measure μ on V is interpreted in strong operator topology, and $\int F^\dagger(v) F(v) \mu(dv) = I_1$. Every transfer-operator $M : \mathfrak{A}_2 \rightarrow \mathfrak{A}_1$ for $\mathfrak{A}_2 = \mathcal{B}(\mathcal{H})$ can be represented by the integral (A.4) with respect to $dv \subseteq V$ of some ideal measure $\Pi(dv)$.

REFERENCES

- [1] V. P. Belavkin. Optimal linear random filtration of quantum boson signals. *Problems of Control and Information Theory*, 3:47–62, 1974.
- [2] V. P. Belavkin. Operational theory of quantum stochastic processes. In *Proc of VIIth Conference on Coding Theory and Information Transmission*, volume 1, pages 23–28, Moscow–Vilnius, 1978.
- [3] V. P. Belavkin. Optimal quantum filtration of markovian signals. *Problems of Control and Information Theory*, 7(5):345–360, 1978.
- [4] V. P. Belavkin. Quantum statistical theory of control. In *Proc. of U S S R Conference on the Control of Laser Radiation*, volume 2, pages 19–23, Tashkent, 1978.
- [5] V. P. Belavkin. Optimal measurement and control in quantum dynamical systems. Technical Report 411, Instytut Fizyki, Copernicus University, Torun', 1979.
- [6] V. P. Belavkin. Optimization of quantum observation and control. In *Notes in Control and Inform Sci, Proc of 9th IFIP Conf on Optimizat Techn, Warszawa 1979*, volume 1, pages 141–149. Springer-Verlag, 1980.
- [7] R. Bellman. *Dynamic Programming*. Princeton Univ. Press, Princeton, New Jersey, 1957.
- [8] A. G. Butkovskii and Y. I. Samoilenko. Controlability of quantum systems. *Dokl. Akad. Nauk SSSR*, 250(1):51–55, 1980.
- [9] A. G. Butkovskii and Y. I. Samoilenko. Control of quantum systems. *Avtomat. Telemekh.*, pages 5–25, 1979.
- [10] E. V. Davies. Quantum communication systems. *IEEE Trans. Inf. Theory*, IT-23:530–534, 1977.
- [11] J. Dixmier. *Les Algebres D'Operateurs Dans L'Espace Hilbertien*. Gauthier-Villars, Paris, 1969.
- [12] G. G. Emch. *Algebraic Methods in Statistical Mechanics and Quantum Field Theory*. Wiley-Interscience, New York, 1972.
- [13] E. S. Ingarden. Quantum information theory. In *Preprint No. 317, Inst. Phys. UMK, Torun*, 1975.
- [14] A. N. Kolmogorov. *Fundamental Concepts of Probability Theory [in Russian]*. Nauka, Moscow, 1974.
- [15] A. A. Krasovskii. Ultimate precision of microcontrol. *Avtomat. Telemekh.*, 12:27–39, 1973.
- [16] A. A. Krasovskii. Ultimate precision of microobservation and microcontrol. *Tekh. Kibernet.*, 3:177–187, 1974.

- [17] L. D. Landau and E. M. Lifshits. *Principles of Quantum Mechanics [in Russian]*. Fizmatgiz, Moscow, 1963.
- [18] J. V. Neumann. *Mathematical Foundations of Quantum Mechanics*. Princeton Univ. Press, Princeton, New Jersey, 1955.
- [19] Y. I. Samoilenko. Electromagnetic control of charged particles with allowance for stochastic and quantum effects. *Controllable Stochastic Processes and Systems [in Russian]*, pages 120–140, 1972.
- [20] R. L. Stratonovich. Conditional markov processes. *Teor. Veroyatn. Primen.*, pages 172–195, 1960.

MOSCOW INSTITUTE OF ELECTRONICS AND MATHEMATICS, 3/12 B. VUZOVSKI PER. MOSCOW 109028, USSR